

Radio Features:

- 160 through 6 Meters - SSB/CW/FM/AM/RTTY/PSK
- 200 Watts of Solid Performance
- Double Conversion Circuit Configuration, 1st IF is set at 9 MHz
- Extra Sharp Crystal Roofing Filter 300 Hz, 600 Hz and 3 kHz
- Totally Independent Second Receiver (VFO-B)
- Large-area 10MHz OCXO Reference Oscillator
- 32-bit High Speed Floating Point DSP, TMS320C6727B by Texas Instruments
- IF WIDTH and IF SHIFT provides great QRM Rejection
- CONTOUR, DNR, IF Notch and APF (4-Selectable BW Audio Peak Filter, CW only)
- Variable RF Filter (VRF) included
- High Speed Automatic Antenna Tuner included
- DMU-2000 External Data Management Unit is available (Optional)
- SM-5000 Matching Station Monitor with stereo speaker system is available (Optional)
- u-Tuning Kit that was developed for the FT DX 9000 is available (Optional)

Supplied Accessories:

Hand Microphone (MH-31B8)
Remote Control Keypad (FH-2)
AC Power Cord
Operating Manual
Warranty Card

Specifications:

Frequency Ranges:	RX	30 kHz - 60 MHz (operating) 1.8MHz - 54 MHz (specified performance, amateur bands only), Except the 9 MHz
	TX	1.8MHz - 54 MHz (amateur bands only)
Circuit Type:	Double-conversion super heterodyne	
Modulation Type:	A1A (CW), A3E (AM), J3E (LSB,USB), F3E (FM), F1B (RTTY), F1D (PACKET),F2D (PACKET)	
Power Output:	10 - 200 Watts (5 - 50 Watts AM carrier)	
Case Size(W x H x D):	462 x 135 x 389 mm	w/o knob and connector
Weight:	21 kg	
Qty in Master Carton:	1	
Warranty:	2 Year	

