

ALINCO

UHF FM Handheld Transceiver

DJ-446

License-Free
PMR446

FEATURES

- 8 frequencies
- 312 channel modes
- 30 memory channels
- 500mW output power
- Battery level indicator
- Switchable hi-low power
- CTCSS on/off
(39 tones per frequency)

The Power to Perform

The ALINCO DJ-446 heavy duty handheld radio is packed with features that make it the ideal choice for business, professional and reliable leisure use. High quality design and construction ensure the best possible performance and reliability. Outstanding audio clarity and receiver specifications ensure maximum range. The DJ-446 is factory programmed with all 8 PMR 446 channels. Each channel has 39 CTCSS tones giving an effective 312 usable channel modes.

- Channel monitor
- Private call channel
- Time out timer
- Bell function
- Memory scan
- Channel scan
- Auto power off
- Power save mode
- Optional desk top quick charger
- Thin type Ni-MH battery
(700mAh, 9.6V)
- Channel finder feature



■ SPECIFICATION

«GENERAL»

Frequency : PMR 446 8 channels

Modulation : F3E

DC Power source : 7-16V (Internal Battery)

Dimensions : 56(W) x 124(H) x 37.5(D)

Weight : approx. 300g

«Transmitter»

Output Power : approx. 500mW

Modulator : Variable reactance

«Receiver»

Configuration : Double conversion super heterodyne

I.F. : 1st : 45.1MHz/2nd : 455kHz

Sensitivity : Better than -12dB μ (12dB SINAD)

AF output : not less than 200mW (10% dist. At 8 Ω)

■ OPTIONS

Headset with VOX : EME-12 (Ear pad type)

Headset with VOX : EME-13 (Earphone type)

Tie-pin mic. : EME-15

And earphone with VOX

Speaker Microphone : EMS-9

Ni-MH Pack : EBP-51N (1500mA)

EDC-36 : Mobile Cigarette lighter adapter
with active noise filter

EDC-37 : External DC supply cable

EME-6 : Earphone

EBC-6 : Mobile bracket